



BOSCH

Message Implementation Guideline

IFTSTA

based on

IFTSTA

International multimodal status report message

UN D.01C S3

Version: D.01C V5
Variant: Status message for LSP Services
Issue date: 25.07.2023
Author: BD/PO11
Contact: EAI.SolutionCenter1@de.bosch.com



Status message for LSP services

Structure / Table of Contents

Counter	No	Tag	St	MaxOcc	Level	Content
0000	1	UNA	C	1	0	Service string advice
0000	2	UNB	M	1	0	Interchange header
0010	3	UNH	M	1	0	Message header
0020	4	BGM	M	1	0	Beginning of message
0030	5	DTM	R	9	1	Date/time/period
0040	6	TSR	R	1	0	Transport service requirements
0050		SG1	R	1	1	Document sender
0060	7	NAD	M	1	1	Name and address
0050		SG1	R	1	1	Message recipient
0060	8	NAD	M	1	1	Name and address
0160		SG4	M	99999	1	Once per LSP LOAD/ LSP Transport Order combination
0170	9	CNI	M	1	1	Consignment information
0200		SG5	M	99	2	Status level
0210	10	STS	M	1	2	Status
0220	11	RFF	D	1	3	House Bill of Lading (HBL)
0220	12	RFF	D	1	3	Master Bill of Lading (MBL)
0220	13	RFF	D	1	3	House AirWay Bill (HAWB)
0220	14	RFF	D	1	3	Master AirWay Bill (MAWB)
0220	15	RFF	C	99	3	Packing list (PL)
0220	16	RFF	C	1	3	Booking reference number (BN)
0220	17	RFF	D	1	3	Equipment number (EQ)
0220	18	RFF	D	99	3	Shipment reference number (SRN)
0220	19	RFF	D	99	3	Delivery note number (DQ)
0220	20	RFF	C	99	3	Customer reference number (CR)
0220	21	RFF	D	99	3	Purchase order number (ON)
0220	22	RFF	D	99	3	Commercial invoice number (IV)
0220	23	RFF	C	1	3	Movement reference number (MRN)
0220	24	RFF	C	1	3	Customs tarif code (ABT)
0220	25	RFF	C	1	3	China customs advanced manifest
0220	26	RFF	D	1	3	Incoterm (TOD)
0220	27	RFF	D	1	3	Incoterm place of terms (LOC)
0220	28	RFF	C	1	3	Warehouse reference code (WR)
0220	29	RFF	C	1	3	Reference to iStar number
0220	30	RFF	C	1	3	Reference to carrier transport identification
0220	31	RFF	D	1	3	TO Id
0220	32	RFF	D	1	3	Load Id
0220	33	RFF	R	1	3	Contract
0230	34	DTM	D	1	3	Actual date/time

Counter = Counter of segment/group within the standard
 No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)



Status message for LSP services

Structure / Table of Contents

Counter	No	Tag	St	MaxOcc	Level	Content
0230	35	DTM	D	1	3	Estimated date/time
0230	36	DTM	D	1	3	Requested date of departure (Planned time of departure PTD)
0230	37	DTM	D	1	3	Requested date of delivery/arrival (Planned time of arrival PTA)
0250	38	FTX	C	1	3	Freertext for transport information
0250	39	FTX	C	1	3	End point of the Geo data provider
0250	40	FTX	D	1	3	Secured Transport (Y/N)
0250	41	FTX	D	1	3	Customs clearance export by Carrier (Y/N)
0250	42	FTX	D	1	3	Customs clearance import by Carrier (Y/N)
0260		SG6	R	1	3	Pick-up Location
0270	43	NAD	M	1	3	Name and address
0260		SG6	R	1	3	Delivery location
0270	44	NAD	M	1	3	Name and address
0260		SG6	C	1	3	Consignor
0270	45	NAD	M	1	3	Name and address
0260		SG6	C	1	3	Consignee
0270	46	NAD	M	1	3	Name and address
0260		SG6	R	1	3	Freight charges payer
0270	47	NAD	M	1	3	Name and address
0260		SG6	C	1	3	Subcontractor
0270	48	NAD	M	1	3	Name and address
0260		SG6	D	1	3	Received-from (Address of status creation)
0270	49	NAD	M	1	3	Name and address
0260		SG6	D	1	3	Event location (Port of loading)
0270	50	NAD	M	1	3	Name and address
0260		SG6	D	1	3	Event location (Port of Discharge)
0270	51	NAD	M	1	3	Name and address
0260		SG6	C	1	3	Consolidator address information
0270	52	NAD	M	1	3	Name and address
0260		SG6	C	1	3	Customs broker
0270	53	NAD	M	1	3	Name and address
0260		SG6	C	1	3	Freight Forwarder
0270	54	NAD	M	1	3	Name and address
0260		SG6	C	1	3	Carrier
0270	55	NAD	M	1	3	Name and address
0310	56	LOC	C	1	3	Geo coordinates
0330		SG8	C	1	3	Transport details
0340	57	TDT	M	1	3	Details of transport

Counter = Counter of segment/group within the standard
 No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)



Status message for LSP services

Structure / Table of Contents

Counter	No	Tag	St	MaxOcc	Level	Content
0400		SG10	C	99	3	Equipment
0410	58	EQD	M	1	3	Equipment details
0420	59	MEA	R	1	4	Gross weight
0420	60	MEA	R	1	4	Chargeable weight
0420	61	MEA	R	1	4	Volume
0440	62	SEL	C	1	4	Seal number
0570		SG14	C	99	3	Goods item details
0580	63	GID	M	1	3	Goods item details
0590	64	HAN	C	1	4	Handling instructions
0610	65	DGS	C	9	4	Dangerous goods
0620	66	FTX	C	10	4	Dangerous goods additional information
0630		SG15	R	1	4	Gross weight
0640	67	MEA	M	1	4	Measurements
0630		SG15	R	1	4	Volume
0640	68	MEA	M	1	4	Measurements
0660		SG16	R	1	4	Dimensions
0670	69	DIM	M	1	4	Dimensions
0690		SG17	R	1	4	Article number customer list
0700	70	PCI	M	1	4	Package identification
0710	71	GIN	R	9999	5	Goods identity number
0690		SG17	C	1	4	Position reference number
0700	72	PCI	M	1	4	Package identification
0690		SG17	C	1	4	Packaging material number
0700	73	PCI	M	1	4	Package identification
0690		SG17	C	999	4	Package identification
0700	74	PCI	M	1	4	Package identification
0710	75	GIN	C	1	5	Goods identity number
0720	76	UNT	M	1	0	Message trailer
0000	77	UNZ	M	1	0	Interchange trailer

Important!! UNH-UNT can only be repeated if there's a change in NAD+MR or NAD+MS!!

Please use UTC for each date/time information!!

Counter = Counter of segment/group within the standard
 No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0000	1	UNA	C	1	0	Service string advice

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
UNA				
UNA1	Component data element separator	M an1	M an1	
UNA2	Data element separator	M an1	M an1	
UNA3	Decimal notation	M an1	M an1	
UNA4	Release indicator	M an1	M an1	
UNA5	Reserved for future use	M an1	M an1	
UNA6	Segment terminator	M an1	M an1	

Remark:

Example:

UNA:+. ? ' |

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0000	2	UNB	M	1	0	Interchange header

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
UNB				
S001	Syntax identifier	M	M	
0001	Syntax identifier	M a4	M a4	UNOC UN/EDC level C
0002	Syntax version number	M n1	M n1	3 Version 3
S002	Interchange sender	M	M	
0004	Sender identification	M an..35	M an..35	Carrier ID
0007	Partner identification code qualifier	C an..4	N	Not used
0008	Address for reverse routing	C an..14	N	Not used
S003	Interchange recipient	M	M	
0010	Recipient identification	M an..35	M an..35	Fix value "LSP_Services"
0007	Partner identification code qualifier	C an..4	N	Not used
0014	Routing address	C an..14	N	Not used
S004	Date/time of preparation	M	M	
0017	Date of preparation	M n6	M n6	
0019	Time of preparation	M n4	M n4	
0020	Interchange control reference	M an..14	M an..14	
S005	Recipient's reference, password	C	N	
0022	Recipient's reference/password	M an..14	N	Not used
0025	Recipient's reference/password qualifier	C an2	N	Not used
0026	Application reference	C an..14	N	Not used
0029	Processing priority code	C a1	N	Not used
0031	Acknowledgement request	C n1	N	Not used
0032	Communications agreement ID	C an..35	N	Not used
0035	Test indicator	C n1	N	Not used

Remark:

Example:

UNB+UNOC:3+Carrier ID+LSP_Services+151202:1033+3518'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0010	3	UNH	M	1	0	Message header

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
UNH				
0062	Message reference number	M an..14	M an..14	
S009	Message identifier	M	M	
0065	Message type	M an..6	M an..6	IFTSTA International multimodal status report message
0052	Message version number	M an..3	M an..3	D Draft version/UN/EDIFACT Directory
0054	Message release number	M an..3	M an..3	01C Release 2001 - C
0051	Controlling agency	M an..2	M an..2	UN UN/CEFACT
0057	Association assigned code	C an..6	N	Not used
0068	Common access reference	C an..35	N	Not used
S010	Status of the transfer	C	N	Not used
0070	Sequence of transfers	M n..2	N	Not used
0073	First and last transfer	C a1	N	Not used

Remark:

Example:

UNH+1+IFTSTA:D:01C:UN'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0020	4	BGM	M	1	0	Beginning of message

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
BGM				
C002	Document/message name	C	C	
1001	Document name code	C an..3	C an..3	7 Process data report
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
1000	Document name	C an..35	N	Not used
C106	Document/message identification	C	R	
1004	Document identifier	C an..35	R an..35	In case of order electronically recieved via IFCSUM by RB: provide same number back (SAP-FPA) In case of order manully received without IFCSUM by RB, provide back the carrier process number
1056	Version identifier	C an..9	N	Not used
1060	Revision identifier	C an..6	N	Not used
1225	Message function code	C an..3	D an..3	Mandatory in case of status code S00 (see STS_4405) 5 Replace 9 Original 40 Request for deletion
4343	Response type code	C an..3	N	Not used

Remark:

Example:

BGM+7+78901234+9'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0030	5	DTM	R	9	1	Date/time/period

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DTM				
C507	Date/time/period	M	M	
2005	Date or time or period function code qualifier	M an..3	M an..3	137 Document/message date/time
2380	Date or time or period value	C an..35	R an..35	message date
2379	Date or time or period format code	C an..3	R an..3	102 CCYYMMDD

Remark:

Example:

DTM+137:20200722:102'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0040	6	TSR	R	1	0	Transport service requirements

Standard			Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
TSR					
C536	Contract and carriage condition	C	R		
4065	Contract and carriage condition code	M an..3	M an..3	10 Port to port 24 Blocked Space Agreement (BSA) 27 Door-to-door 28 Origin door to destination port 29 Destination port to destination door 30 Origin door to origin port 31 Origin port to destination door	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
C233	Service	C	R		
7273	Service requirement code	M an..3	M an..3	AIR SEA TRUCK RAIL	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
7273	Service requirement code	C an..3	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
C537	Transport priority	C	R		
4219	Transport service priority code	M an..3	M an..3	A means AIR => A0x S means SEA => S0x R means RAIL => R0x T means TRUCK => T0x A01 EMERGENCY A02 CRITICAL A03 STANDARD A04 NFO (Next flight out) S01 FCL/FCL/FCL S02 LCL/FCL/FCL S03 LCL/LCL/LCL R01 FCL/FCL/FCL R02 LCL/FCL/FCL R03 LCL/LCL/LCL T01 FTL T02 LTL	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
C703	Nature of cargo	C	N		
7085	Cargo type classification code	M an..3	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	

No = Consecutive segment number
MaxOcc = Maximum occurrence of the segment/group
Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
O=Optional, F=Floating, D=Dependent, A=Advised,
S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Remark:

Example:

TSR+27+AIR+A03'

No = Consecutive segment number
MaxOcc = Maximum occurrence of the segment/group
Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
O=Optional, F=Floating, D=Dependent, A=Advised,
S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0050		SG1	R	1	1	Document sender
0060	7	NAD	M	1	1	Name and address

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
NAD				
3035	Party function code qualifier	M an..3	M an..3	MS Document/message issuer/sender
C082	Party identification details	C	R	
3039	Party identifier	M an..35	R an..35	
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C058	Name and address	C	N	
3124	Name and address description	M an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
C080	Party name	C	C	
3036	Party name	M an..35	M an..35	
3036	Party name	C an..35	C an..35	
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3045	Party name format code	C an..3	N	Not used
C059	Street	C	C	
3042	Street and number or post office box identifier	M an..35	M an..35	
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3164	City name	C an..35	C an..35	
C819	Country sub-entity details	C	N	
3229	Country sub-entity name code	C an..9	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3228	Country sub-entity name	C an..70	N	Not used
3251	Postal identification code	C an..17	C an..17	
3207	Country name code	C an..3	C an..3	country code e.g. DE GERMANY

Remark:

Example:

NAD+MS+GS1COMPANYID++CARRIER COMPANY:EDI+STREET+CITY++12345+DE'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0050		SG1	R	1	1	Message recipient
0060	8	NAD	M	1	1	Name and address

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
NAD				
3035	Party function code qualifier	M an..3	M an..3	MR Message recipient
C082	Party identification details	C	N	
3039	Party identifier	M an..35	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C058	Name and address	C	N	
3124	Name and address description	M an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
C080	Party name	C	C	
3036	Party name	M an..35	M an..35	
3036	Party name	C an..35	C an..35	
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3045	Party name format code	C an..3	N	Not used
C059	Street	C	C	
3042	Street and number or post office box identifier	M an..35	M an..35	
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3164	City name	C an..35	C an..35	
C819	Country sub-entity details	C	N	
3229	Country sub-entity name code	C an..9	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3228	Country sub-entity name	C an..70	N	Not used
3251	Postal identification code	C an..17	C an..17	
3207	Country name code	C an..3	C an..3	country code e.g. DE GERMANY

Remark:

Example:

NAD+MR+++ROBERT BOSCH GMBH:ZENTRALLAGER DEUTSCHLAND+MITTELRHEINSTR. 19+WORMS++67550+DE'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0160		SG4	M	99999	1	Once per LSP LOAD/ LSP Transport Order combination
0170	9	CNI	M	1	1	Consignment information

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
CNI				
1490	Consolidation item number	C n..4	R n..4	Incrementing counter
C503	Document/message details	C	R	
1004	Document identifier	C an..35	R an..35	Combination "LSP LOAD/ LSP Transport Order", for example 12345-ABC7890123 If LSP LOAD not available, then provide default value "00000" as LSP LOAD, for example 00000-ABC7890123 If IFCSUM received from Bosch, to be taken from IFCSUM (CNI)
1373	Document status code	C an..3	N	Not used
1366	Document source description	C an..70	N	Not used
3453	Language name code	C an..3	N	Not used
1056	Version identifier	C an..9	N	Not used
1060	Revision identifier	C an..6	N	Not used
1312	Consignment load sequence identifier	C n..4	N	Not used

Remark:

Example:

CNI+1+12345-ABC7890123'

CNI+1+PR1-0073252032'

same content as sent in IFCSUM (CNI)

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0210	10	STS	M	1	2	Status

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
STS				
C601	Status category	C	C	
9015	Status category code	M an..3	M an..3	1 Transport
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C555	Status	C	R	
4405	Status description code	M an..3	R an..3	for value list please see APPENDIX 3
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
4404	Status description	C an..35	N	Not used
C556	Status reason	C	D	Required in case of status S09, and for all other status codes depending on the situation
9013	Status reason description code	M an..3	M an..3	for value list please see APPENDIX 2
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
9012	Status reason description	C an..256	C an..256	
C556	Status reason	C	N	
9013	Status reason description code	M an..3	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
9012	Status reason description	C an..256	N	Not used
C556	Status reason	C	N	
9013	Status reason description code	M an..3	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
9012	Status reason description	C an..256	N	Not used
C556	Status reason	C	N	
9013	Status reason description code	M an..3	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
9012	Status reason description	C an..256	N	Not used
C556	Status reason	C	N	
9013	Status reason description code	M an..3	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
9012	Status reason description	C an..256	N	Not used

Remark:

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Example:

STS+1+S02+C05:::Reason code text'

No = Consecutive segment number
MaxOcc = Maximum occurrence of the segment/group
Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
O=Optional, F=Floating, D=Dependent, A=Advised,
S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	11	RFF	D	1	3	House Bill of Lading (HBL)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	HB HBL reference
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Required in case of Sea transport

Example:

RFF+HB:HAMA55045'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	12	RFF	D	1	3	Master Bill of Lading (MBL)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	BL BL reference
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Required in case of Sea transport

Example:

RFF+BL: COSU6257279340'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	13	RFF	D	1	3	House AirWay Bill (HAWB)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	HA HAWB reference
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Required in case of Air transport

Example:

RFF+HA:232323'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	14	RFF	D	1	3	Master AirWay Bill (MAWB)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	MA MAWB reference
1154	Reference identifier	C an..70	R an11	3 digits IATA airline code, 8-digits MAWB number
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Required in case of Air transport

Example:

RFF+MA:15746714673'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	15	RFF	C	99	3	Packing list (PL)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	PL Packing list
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Example:

RFF+PL:121212'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	16	RFF	C	1	3	Booking reference number (BN)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	BN Booking reference number
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Example:

RFF+BN:12AB34CD'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	17	RFF	D	1	3	Equipment number (EQ)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	EQ Equipment number
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Required in case of Sea transport

Example:

RFF+EQ:TEMU6982560'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	18	RFF	D	99	3	Shipment reference number (SRN)

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
RFF					
C506	Reference	M	M		
1153	Reference code qualifier	M an..3	M an..3	SRN Shipment reference number	
1154	Reference identifier	C an..70	R an..70		
1156	Document line identifier	C an..6	N	Not used	
4000	Reference version identifier	C an..35	N	Not used	
1060	Revision identifier	C an..6	N	Not used	

Remark:

Required when received via IFCSUM (RFF-SRN)

Example:

RFF+SRN:SHD-97673'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	19	RFF	D	99	3	Delivery note number (DQ)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	DQ Delivery note number
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Required for status codes S00 and S02 (SG5_STS)

If IFCSUM received from Bosch, to be taken from IFCSUM (RFF+DQ)

Example:

RFF+DQ: 5/SEXP/20/WZ '

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	20	RFF	C	99	3	Customer reference number (CR)

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
RFF					
C506	Reference	M	M		
1153	Reference code qualifier	M an..3	M an..3	CR Customer reference number	
1154	Reference identifier	C an..70	R an..70		
1156	Document line identifier	C an..6	N	Not used	
4000	Reference version identifier	C an..35	N	Not used	
1060	Revision identifier	C an..6	N	Not used	

Remark:

If IFCSUM received from Bosch, to be taken from IFCSUM (RFF+CR)

Example:

RFF+CR:20008868992B01017115'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	21	RFF	D	99	3	Purchase order number (ON)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	ON Order number (purchase)
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	R an..6	
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Required for status codes S00 and S02 (SG5_STS)

Example:

RFF+ON:4200001234:0001'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	22	RFF	D	99	3	Commercial invoice number (IV)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	IV Invoice number
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Required for status codes S00 and S02 (SG5_STS)
 If IFCSUM received from Bosch, to be taken from IFCSUM (RFF-IV)

Example:

RFF+IV:5/SEXP/01/20/FV'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	23	RFF	C	1	3	Movement reference number (MRN)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	MRN Movement reference number
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Example:

RFF+MRN:20DE755324047503E6'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	24	RFF	C	1	3	Customs tariff code (ABT)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	ABT Customs declaration number
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

If IFCSUM received from Bosch, to be taken from IFCSUM (RFF-ABT)

Example:

RFF+ABT:ATB150059680320202325/3'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	25	RFF	C	1	3	China customs advanced manifest

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	CC China customs advanced manifest
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Example:

RFF+CC:ATB150059680320202325/3'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	26	RFF	D	1	3	Incoterm (TOD)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	TOD Incoterm
1154	Reference identifier	C an..70	R an..70	Incoterm EXW (Ex works) is forbidden at Robert Bosch GmbH
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Required for status codes S00 and S02 (SG5_STS)

Example:

RFF+TOD:FCA'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	27	RFF	D	1	3	Incoterm place of terms (LOC)

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
RFF					
C506	Reference	M	M		
1153	Reference code qualifier	M an..3	M an..3	LOC Incoterm place of terms	
1154	Reference identifier	C an..70	R an..70		
1156	Document line identifier	C an..6	N	Not used	
4000	Reference version identifier	C an..35	N	Not used	
1060	Revision identifier	C an..6	N	Not used	

Remark:

Required if Incoterm has to be transmitted

Example:

RFF+LOC:Hamburg'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	28	RFF	C	1	3	Warehouse reference code (WR)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	WR Warehouse receipt number
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Example:

RFF+WR: I-26943525'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	29	RFF	C	1	3	Reference to iStar number

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	ATT Exceptional transport authorisation number
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Example:

RFF+ATT:bbuf909911sfd'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	30	RFF	C	1	3	Reference to carrier transport identification

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	needs to be unique FF Freight forwarder's reference number
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Reference to carrier transport identification, could also be flight or vessel identification

Example:

RFF+FF:04310394173'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	31	RFF	D	1	3	TO Id

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	TO Transport Order Id
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Mandatory in case of TMC transports

Example:

RFF+TO:676767'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	32	RFF	D	1	3	Load Id

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	LO Load ID
1154	Reference identifier	C an..70	R an..70	
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Mandatory in case of TMC transports

Example:

RFF+LO:787878'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0220	33	RFF	R	1	3	Contract

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	Reference	M	M	
1153	Reference code qualifier	M an..3	M an..3	CT Contract number
1154	Reference identifier	C an..70	R an..70	if shipment is non contracted (e.g. SPOT), please fill this field with "NON-CONTRACTED" or "SPOT"
1156	Document line identifier	C an..6	N	Not used
4000	Reference version identifier	C an..35	N	Not used
1060	Revision identifier	C an..6	N	Not used

Remark:

Example:

RFF+CT:NON-CONTRACTED'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0230	34	DTM	D	1	3	Actual date/time

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DTM				
C507	Date/time/period	M	M	
2005	Date or time or period function code qualifier	M an..3	M an..3	9 Processing date/time
2380	Date or time or period value	C an..35	R an..35	Actual date/time for the status
2379	Date or time or period format code	C an..3	R an..3	203 CCYYMMDDHHMM

Remark:

Required if DTM+76 is missing

Linked to content of SG5-ST5 "Status Code"

Example:

DTM+9:202004141316:203'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0230	35	DTM	D	1	3	Estimated date/time

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DTM				
C507	Date/time/period	M	M	
2005	Date or time or period function code qualifier	M an..3	M an..3	76 Date/time, scheduled for
2380	Date or time or period value	C an..35	R an..35	Estimated date/time for the status
2379	Date or time or period format code	C an..3	R an..3	203 CCYYMMDDHHMM

Remark:

Required if DTM+9 is missing

Linked to content of SG5-ST5 "Status Code"

Example:

DTM+76:202004151316:203'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
	0200	SG5	M	99	2	Status level
	0230	DTM	D	1	3	Requested date of departure (Planned time of departure PTD)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DTM				
C507	Date/time/period	M	M	
2005	Date or time or period function code qualifier	M an..3	M an..3	11 Despatch date and or time
2380	Date or time or period value	C an..35	R an..35	
2379	Date or time or period format code	C an..3	R an..3	203 CCYYMMDDHHMM

Remark:

Mandatory only for status S00

Responsible: LSP1 for Door-to-Door/ Door-to-Port

Responsible: LSP2 for Port-to-Door

start point related to NAD+PW (pickup location)

start point related to NAD+PW (on hand origin port, airport)

Example:

DTM+11:202004151316:203'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0230	37	DTM	D	1	3	Requested date of delivery/arrival (Planned time of arrival PTA)

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DTM				
C507	Date/time/period	M	M	
2005	Date or time or period function code qualifier	M an..3	M an..3	2 Delivery date/time, requested
2380	Date or time or period value	C an..35	R an..35	
2379	Date or time or period format code	C an..3	R an..3	203 CCYYMMDDHHMM

Remark:

Mandatory only for status S00

Responsible: LSP1 for Door-to-Door/ Door-to-Port

Responsible: LSP2 for Port-to-Door

end point related to NAD+DP (delivery place/ on hand destination port, airport)

end point related to NAD+DP (delivery place)

Example:

DTM+2:202004151316:203'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0250	38	FTX	C	1	3	Freetext for transport information

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
FTX					
4451	Text subject code qualifier	M an..3	M an..3	TRA Transportation information	
4453	Free text function code	C an..3	N	Not used	
C107	Text reference	C	N	Not used	
4441	Free text description code	M an..17	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
C108	Text literal	C	R	Not used	
4440	Free text	M an..512	M an..512	Free text comment	
4440	Free text	C an..512	N	Not used	
4440	Free text	C an..512	N	Not used	
4440	Free text	C an..512	N	Not used	
4440	Free text	C an..512	N	Not used	
3453	Language name code	C an..3	N	Not used	
4447	Free text format code	C an..3	N	Not used	

Remark:

Example:

FTX+TRA+++Free text comment'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0250	39	FTX	C	1	3	End point of the Geo data provider

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
FTX					
4451	Text subject code qualifier	M an..3	M an..3	AGK Equipment	
4453	Free text function code	C an..3	N	Not used	
C107	Text reference	C	N	Not used	
4441	Free text description code	M an..17	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
C108	Text literal	C	R	Not used	
4440	Free text	M an..512	M an..512	Free text comment	
4440	Free text	C an..512	N	Not used	
4440	Free text	C an..512	N	Not used	
4440	Free text	C an..512	N	Not used	
4440	Free text	C an..512	N	Not used	
3453	Language name code	C an..3	N	Not used	
4447	Free text format code	C an..3	N	Not used	

Remark:

Example:

FTX+AGK+++http?://www.ednpoint-dp.com'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0250	40	FTX	D	1	3	Secured Transport (Y/N)

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
FTX				
4451	Text subject code qualifier	M an..3	M an..3	SAF Safety information
4453	Free text function code	C an..3	N	Not used
C107	Text reference	C	N	
4441	Free text description code	M an..17	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C108	Text literal	C	R	
4440	Free text	M an..512	M an..512	Y Yes N No
4440	Free text	C an..512	N	Not used
4440	Free text	C an..512	N	Not used
4440	Free text	C an..512	N	Not used
4440	Free text	C an..512	N	Not used
3453	Language name code	C an..3	N	Not used
4447	Free text format code	C an..3	N	Not used

Remark:

Mandatory in case of status code S02 (see STS_4405)

Example:

FTX+SAF+++Y'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0250	41	FTX	D	1	3	Customs clearance export by Carrier (Y/N)

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
FTX				
4451	Text subject code qualifier	M an..3	M an..3	CEX Customs clearance instructions export
4453	Free text function code	C an..3	N	Not used
C107	Text reference	C	N	
4441	Free text description code	M an..17	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C108	Text literal	C	R	
4440	Free text	M an..512	M an..512	Y Yes N No
4440	Free text	C an..512	N	Not used
4440	Free text	C an..512	N	Not used
4440	Free text	C an..512	N	Not used
4440	Free text	C an..512	N	Not used
3453	Language name code	C an..3	N	Not used
4447	Free text format code	C an..3	N	Not used

Remark:

Mandatory in case of status code S02 (see STS_4405)

Example:

FTX+CEX+++Y'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0250	42	FTX	D	1	3	Customs clearance import by Carrier (Y/N)

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
FTX				
4451	Text subject code qualifier	M an..3	M an..3	CIP Customs clearance instruction import
4453	Free text function code	C an..3	N	Not used
C107	Text reference	C	N	
4441	Free text description code	M an..17	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C108	Text literal	C	R	
4440	Free text	M an..512	M an..512	Y Yes N No
4440	Free text	C an..512	N	Not used
4440	Free text	C an..512	N	Not used
4440	Free text	C an..512	N	Not used
4440	Free text	C an..512	N	Not used
3453	Language name code	C an..3	N	Not used
4447	Free text format code	C an..3	N	Not used

Remark:

Mandatory in case of status code S02 (see STS_4405)

Example:

FTX+CIP+++Y'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	R	1	3	Pick-up Location
0270	43	NAD	M	1	3	Name and address

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
NAD					
3035	Party function code qualifier	M an..3	M an..3	PW Despatch party	
C082	Party identification details	C	R		
3039	Party identifier	M an..35	R an..35		
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
C058	Name and address	C	R		
3124	Name and address description	M an..35	M an..35		
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
C080	Party name	C	D		
3036	Party name	M an..35	M an..35	for value list please see APPENDIX 1	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3045	Party name format code	C an..3	N	Not used	
C059	Street	C	D		
3042	Street and number or post office box identifier	M an..35	M an..35		
3042	Street and number or post office box identifier	C an..35	N	Not used	
3042	Street and number or post office box identifier	C an..35	N	Not used	
3042	Street and number or post office box identifier	C an..35	N	Not used	
3164	City name	C an..35	D an..35		
C819	Country sub-entity details	C	N		
3229	Country sub-entity name code	C an..9	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
3228	Country sub-entity name	C an..70	N	Not used	
3251	Postal identification code	C an..17	D an..17		
3207	Country name code	C an..3	D an..3	country code e.g. FR FRANCE	

Remark:

all elements with D=Dependent are required for status events starting from S45

Example:

NAD+PW+989898+name+description as depot ID+address+city++postal code+FR'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	R	1	3	Delivery location
0270	44	NAD	M	1	3	Name and address

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
NAD				
3035	Party function code qualifier	M an..3	M an..3	DP Delivery party
C082	Party identification details	C	R	
3039	Party identifier	M an..35	R an..35	
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C058	Name and address	C	R	
3124	Name and address description	M an..35	M an..35	
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
C080	Party name	C	D	
3036	Party name	M an..35	M an..35	for value list please see APPENDIX 1
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3045	Party name format code	C an..3	N	Not used
C059	Street	C	D	
3042	Street and number or post office box identifier	M an..35	M an..35	
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3164	City name	C an..35	D an..35	
C819	Country sub-entity details	C	N	
3229	Country sub-entity name code	C an..9	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3228	Country sub-entity name	C an..70	N	Not used
3251	Postal identification code	C an..17	D an..17	
3207	Country name code	C an..3	D an..3	country code e.g. FR FRANCE

Remark:

all elements with D=Dependent are required for status events starting from S45

Example:

NAD+DP+444555+name+description as depot ID+address+city++postal code+FR'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	C	1	3	Consignor
0270	45	NAD	M	1	3	Name and address

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
NAD					
3035	Party function code qualifier	M an..3	M an..3	CZ Consignor	
C082	Party identification details	C	R		
3039	Party identifier	M an..35	R an..35		
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
C058	Name and address	C	R		
3124	Name and address description	M an..35	M an..35		
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
C080	Party name	C	D		
3036	Party name	M an..35	M an..35	for value list please see APPENDIX 1	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3045	Party name format code	C an..3	N	Not used	
C059	Street	C	D		
3042	Street and number or post office box identifier	M an..35	M an..35		
3042	Street and number or post office box identifier	C an..35	N	Not used	
3042	Street and number or post office box identifier	C an..35	N	Not used	
3042	Street and number or post office box identifier	C an..35	N	Not used	
3164	City name	C an..35	D an..35		
C819	Country sub-entity details	C	N		
3229	Country sub-entity name code	C an..9	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
3228	Country sub-entity name	C an..70	N	Not used	
3251	Postal identification code	C an..17	D an..17		
3207	Country name code	C an..3	D an..3	country code e.g. FR FRANCE	

Remark:

all elements with D=Dependent are required for status events starting from S45

Example:

NAD+CZ+PLPIW001+name+description as depot ID+address+city++postal code+FR'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	C	1	3	Consignee
0270	46	NAD	M	1	3	Name and address

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
NAD					
3035	Party function code qualifier	M an..3	M an..3	CN Consignee	
C082	Party identification details	C	R		
3039	Party identifier	M an..35	R an..35		
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
C058	Name and address	C	R		
3124	Name and address description	M an..35	M an..35		
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
C080	Party name	C	D		
3036	Party name	M an..35	M an..35	for value list please see APPENDIX 1	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3045	Party name format code	C an..3	N	Not used	
C059	Street	C	D		
3042	Street and number or post office box identifier	M an..35	M an..35		
3042	Street and number or post office box identifier	C an..35	N	Not used	
3042	Street and number or post office box identifier	C an..35	N	Not used	
3042	Street and number or post office box identifier	C an..35	N	Not used	
3164	City name	C an..35	D an..35		
C819	Country sub-entity details	C	N		
3229	Country sub-entity name code	C an..9	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
3228	Country sub-entity name	C an..70	N	Not used	
3251	Postal identification code	C an..17	D an..17		
3207	Country name code	C an..3	D an..3	country code e.g. FR FRANCE	

Remark:

all elements with D=Dependent are required for status events starting from S45

Example:

NAD+CN+CNB005+name+description as depot ID+address+city++postal code+FR'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	R	1	3	Freight charges payer
0270	47	NAD	M	1	3	Name and address

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
NAD					
3035	Party function code qualifier	M an..3	M an..3	FP Freight/charges payer	
C082	Party identification details	C	R		
3039	Party identifier	M an..35	R an..35		
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
C058	Name and address	C	R		
3124	Name and address description	M an..35	M an..35		
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
C080	Party name	C	D		
3036	Party name	M an..35	M an..35	for value list please see APPENDIX 1	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3045	Party name format code	C an..3	N	Not used	
C059	Street	C	D		
3042	Street and number or post office box identifier	M an..35	M an..35		
3042	Street and number or post office box identifier	C an..35	N	Not used	
3042	Street and number or post office box identifier	C an..35	N	Not used	
3042	Street and number or post office box identifier	C an..35	N	Not used	
3164	City name	C an..35	D an..35		
C819	Country sub-entity details	C	N		
3229	Country sub-entity name code	C an..9	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
3228	Country sub-entity name	C an..70	N	Not used	
3251	Postal identification code	C an..17	D an..17		
3207	Country name code	C an..3	D an..3	country code e.g. FR FRANCE	

Remark:

all elements with D=Dependent are required for status events starting from S45

Example:

NAD+FP+CNB005+name+description as depot ID+address+city++postal code+FR'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	C	1	3	Subcontractor
0270	48	NAD	M	1	3	Name and address

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
NAD					
3035	Party function code qualifier	M an..3	M an..3	SC Subcontractor	
C082	Party identification details	C	R		
3039	Party identifier	M an..35	R an..35		
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
C058	Name and address	C	C		
3124	Name and address description	M an..35	M an..35		
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
C080	Party name	C	N		
3036	Party name	M an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3045	Party name format code	C an..3	N	Not used	
C059	Street	C	C		
3042	Street and number or post office box identifier	M an..35	M an..35		
3042	Street and number or post office box identifier	C an..35	N	Not used	
3042	Street and number or post office box identifier	C an..35	N	Not used	
3042	Street and number or post office box identifier	C an..35	N	Not used	
3164	City name	C an..35	C an..35		
C819	Country sub-entity details	C	N		
3229	Country sub-entity name code	C an..9	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
3228	Country sub-entity name	C an..70	N	Not used	
3251	Postal identification code	C an..17	C an..17		
3207	Country name code	C an..3	C an..3	country code e.g. FR FRANCE	

Remark:

Example:

NAD+SC+456789+name++address+city++postal code+FR'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	D	1	3	Received-from (Address of status creation)
0270	49	NAD	M	1	3	Name and address

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
NAD				
3035	Party function code qualifier	M an..3	M an..3	RF Received from
C082	Party identification details	C	C	
3039	Party identifier	M an..35	M an..35	
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C058	Name and address	C	N	
3124	Name and address description	M an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
C080	Party name	C	N	
3036	Party name	M an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3045	Party name format code	C an..3	N	Not used
C059	Street	C	C	
3042	Street and number or post office box identifier	M an..35	M an..35	
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3164	City name	C an..35	C an..35	
C819	Country sub-entity details	C	N	
3229	Country sub-entity name code	C an..9	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3228	Country sub-entity name	C an..70	N	Not used
3251	Postal identification code	C an..17	C an..17	
3207	Country name code	C an..3	C an..3	country code e.g. FR FRANCE

Remark:

Required for status codes: S10 | S11 | S17 | S18 | S12 | S13 | S32 | S50 | S51

Example:

NAD+RF++++address+city++postal code+FR'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	D	1	3	Event location (Port of loading)
0270	50	NAD	M	1	3	Name and address

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
NAD				
3035	Party function code qualifier	M an..3	M an..3	EL Event location
C082	Party identification details	C	R	
3039	Party identifier	M an..35	R an..35	Identifier of event location (e.g. ID, ISO-Code)
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C058	Name and address	C	N	
3124	Name and address description	M an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
C080	Party name	C	C	
3036	Party name	M an..35	M an..35	POL Port of loading
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3045	Party name format code	C an..3	N	Not used
C059	Street	C	N	
3042	Street and number or post office box identifier	M an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3164	City name	C an..35	N	Not used
C819	Country sub-entity details	C	N	
3229	Country sub-entity name code	C an..9	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3228	Country sub-entity name	C an..70	N	Not used
3251	Postal identification code	C an..17	N	Not used
3207	Country name code	C an..3	N	Not used

Remark:

Mandatory only for main carriage leg

Example:

NAD+EL+DEHAM++POL'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	D	1	3	Event location (Port of Discharge)
0270	51	NAD	M	1	3	Name and address

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
NAD				
3035	Party function code qualifier	M an..3	M an..3	EL Event location
C082	Party identification details	C	R	
3039	Party identifier	M an..35	R an..35	Identifier of event location (e.g. ID, ISO-Code)
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C058 Name and address				
3124	Name and address description	M an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
C080 Party name				
3036	Party name	M an..35	M an..35	POD Port of discharge
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3045	Party name format code	C an..3	N	Not used
C059 Street				
3042	Street and number or post office box identifier	M an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3164	City name	C an..35	N	Not used
C819 Country sub-entity details				
3229	Country sub-entity name code	C an..9	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3228	Country sub-entity name	C an..70	N	Not used
3251	Postal identification code	C an..17	N	Not used
3207	Country name code	C an..3	N	Not used

Remark:

Mandatory only for main carriage leg

Example:

NAD+EL+CHSHA++POD'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	C	1	3	Consolidator address information
0270	52	NAD	M	1	3	Name and address

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
NAD					
3035	Party function code qualifier	M an..3	M an..3	CS Consolidator	
C082	Party identification details	C	R		
3039	Party identifier	M an..35	R an..35		
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
C058	Name and address	C	C		
3124	Name and address description	M an..35	M an..35		
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
3124	Name and address description	C an..35	N	Not used	
C080	Party name	C	N		
3036	Party name	M an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3036	Party name	C an..35	N	Not used	
3045	Party name format code	C an..3	N	Not used	
C059	Street	C	C		
3042	Street and number or post office box identifier	M an..35	M an..35		
3042	Street and number or post office box identifier	C an..35	N	Not used	
3042	Street and number or post office box identifier	C an..35	N	Not used	
3042	Street and number or post office box identifier	C an..35	N	Not used	
3164	City name	C an..35	C an..35		
C819	Country sub-entity details	C	N		
3229	Country sub-entity name code	C an..9	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
3228	Country sub-entity name	C an..70	N	Not used	
3251	Postal identification code	C an..17	C an..17		
3207	Country name code	C an..3	C an..3	country code e.g. FR FRANCE	

Remark:

Mandatory only for main carriage leg

Example:

NAD+CS+71019878+name++address+city++postal code+FR'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	C	1	3	Customs broker
0270	53	NAD	M	1	3	Name and address

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
NAD				
3035	Party function code qualifier	M an..3	M an..3	CB Customs broker
C082	Party identification details	C	R	
3039	Party identifier	M an..35	R an..35	
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C058	Name and address	C	C	
3124	Name and address description	M an..35	M an..35	
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
C080	Party name	C	N	
3036	Party name	M an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3045	Party name format code	C an..3	N	Not used
C059	Street	C	C	
3042	Street and number or post office box identifier	M an..35	M an..35	
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3164	City name	C an..35	C an..35	
C819	Country sub-entity details	C	N	
3229	Country sub-entity name code	C an..9	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3228	Country sub-entity name	C an..70	N	Not used
3251	Postal identification code	C an..17	C an..17	
3207	Country name code	C an..3	C an..3	country code e.g. FR FRANCE

Remark:

Example:

NAD+CB+654456+name++address+city++postal code+FR'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	C	1	3	Freight Forwarder
0270	54	NAD	M	1	3	Name and address

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
NAD				
3035	Party function code qualifier	M an..3	M an..3	FW Freight forwarder
C082	Party identification details	C	R	
3039	Party identifier	M an..35	R an..35	
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C058	Name and address	C	C	
3124	Name and address description	M an..35	M an..35	
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
C080	Party name	C	N	
3036	Party name	M an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3045	Party name format code	C an..3	N	Not used
C059	Street	C	C	
3042	Street and number or post office box identifier	M an..35	M an..35	
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3164	City name	C an..35	C an..35	
C819	Country sub-entity details	C	N	
3229	Country sub-entity name code	C an..9	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3228	Country sub-entity name	C an..70	N	Not used
3251	Postal identification code	C an..17	C an..17	
3207	Country name code	C an..3	C an..3	country code e.g. FR FRANCE

Remark:

only for non-TMC transports

Example:

NAD+FW+4546323+name++address+city++postal code+FR'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG6	C	1	3	Carrier
0270	55	NAD	M	1	3	Name and address

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
NAD				
3035	Party function code qualifier	M an..3	M an..3	CA Carrier
C082	Party identification details	C	R	
3039	Party identifier	M an..35	R an..35	
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C058	Name and address	C	C	
3124	Name and address description	M an..35	M an..35	
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
3124	Name and address description	C an..35	N	Not used
C080	Party name	C	N	
3036	Party name	M an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3045	Party name format code	C an..3	N	Not used
C059	Street	C	C	
3042	Street and number or post office box identifier	M an..35	M an..35	
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3042	Street and number or post office box identifier	C an..35	N	Not used
3164	City name	C an..35	C an..35	
C819	Country sub-entity details	C	N	
3229	Country sub-entity name code	C an..9	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3228	Country sub-entity name	C an..70	N	Not used
3251	Postal identification code	C an..17	C an..17	
3207	Country name code	C an..3	C an..3	country code e.g. FR FRANCE

Remark:

Example:

NAD+CA+234245+name++address+city++postal code+FR'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0200		SG5	M	99	2	Status level
0310	56	LOC	C	1	3	Geo coordinates

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
LOC				
3227	Location function code qualifier	M an..3	M an..3	172 Reporting location
C517	Location identification	C	N	
3225	Location name code	C an..35	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3224	Location name	C an..256	N	Not used
C519	Related location one identification	C	C	
3223	First related location name code	C an..25	C an..25	Geo coordinates of location (formatted in notation xx.yy.zzN aa.bb.ccE)
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3222	First related location name	C an..70	N	Not used
C553	Related location two identification	C	N	
3233	Second related location name code	C an..25	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3232	Second related location name	C an..70	N	Not used
5479	Relation code	C an..3	N	Not used

Remark:

Example:

LOC+172++52.49.38N 13.41.37E'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0330		SG8	C	1	3	Transport details
0340	57	TDT	M	1	3	Details of transport

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
TDT				
8051	Transport stage code qualifier	M an..3	M an..3	10 Pre-carriage transport 20 Main-carriage transport 21 Main carriage - first carrier 22 Main carriage - second carrier 23 Main carriage - third carrier
8028	Means of transport journey identifier	C an..17	N	Not used
C220	Mode of transport	C	R	
8067	Transport mode name code	C an..3	R an..3	10 Sea transport 20 Rail transport 30 Road transport 40 Air transport
8066	Transport mode name	C an..17	R an..17	SEA RAIL ROAD AIR
C228	Transport means	C	C	
8179	Transport means description code	C an..8	C an..8	6 Aircraft 13 Ocean vessel 31 Truck
8178	Transport means description	C an..17	C an..17	Sea freight voyage number
C040	Carrier	C	C	
3127	Carrier identifier	C an..17	C an..17	Sea = 4 letter shipping line code (SCAC Code, e.g. MAEU) Air = 2 letter airline code of Airline (e.g. AF)
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3128	Carrier name	C an..35	C an..35	
8101	Transit direction indicator code	C an..3	N	Not used
C401	Excess transportation information	C	N	
8457	Excess transportation reason code	M an..3	N	Not used
8459	Excess transportation responsibility code	M an..3	N	Not used
7130	Customer shipment authorisation identifier	C an..17	N	Not used
C222	Transport identification	C	D	
8213	Transport means identification name identifier	C an..9	D an..9	required for transport name code "30" and "40" and for status events S04, S07, S16 10 Truck License plate number 30 Name of the ship 40 Flight number
1131	Code list identification code	C an..17	N	Not used

No = Consecutive segment number
MaxOcc = Maximum occurrence of the segment/group
Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
O=Optional, F=Floating, D=Dependent, A=Advised,
S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
3055	Code list responsible agency code	C an..3	N	Not used
8212	Transport means identification name	C an..35	C an..35	In case of 30 Name of the ship In case of 40 Flight number without airline code (4-digits)
8453	Transport means nationality code	C an..3	N	Not used
8281	Transport means ownership indicator code	C an..3	N	Not used

Remark:

Example:

Air: TDT+21++40:AIR+6+RU::Lufthansa Cargo+++40::RU 418'

Sea: TDT+21++10:SEA+13:0BX91W+OOLU::DBS+++30::CMA CGM TIGRIS'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
	0400	SG10	C	99	3	Equipment
	0410	58 EQD	M	1	3	Equipment details

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
EQD				
8053	Equipment type code qualifier	M an..3	M an..3	TE Trailer CN Container ZZZ Mutually defined
C237	Equipment identification	C	R	
8260	Equipment identifier	C an..17	R an..17	
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
3207	Country name code	C an..3	N	Not used
C224	Equipment size and type	C	D	
8155	Equipment size and type description code	C an..10	D an..10	required for sea freight BCO and FCL
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	D an..3	5 ISO (International Organization for Standardization)
8154	Equipment size and type description	C an..35	C an..35	
8077	Equipment supplier code	C an..3	N	Not used
8249	Equipment status code	C an..3	N	Not used
8169	Full or empty indicator code	C an..3	C an..3	FLL Full EMT Empty

Remark:

ISO 6346 code is used as 4-digit value

Length (1 digit)	Height (1 digit)	Type (2 digits)
2 – 20 Feet	2 – 8 Feet 6 Inches	G1 – General Purpose Container
4 – 40 Feet	5 – 9 Feet 6 Inches „High Cube“	U1 – Open Top Container
L – 45 Feet		P1 – Platform Container
M – 48 Feet		

Example:

EQD+CN+TEMU6982560+45G1::5:45G1+++FLL'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
	0400	SG10	C	99	3	Equipment
	0420	MEA	R	1	4	Gross weight

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
MEA				
6311	Measurement purpose code qualifier	M an..3	M an..3	WT Weights
C502	Measurement details	C	R	
6313	Measured attribute code	C an..3	R an..3	G Gross weight
6321	Measurement significance code	C an..3	N	Not used
6155	Non-discrete measurement name code	C an..17	N	Not used
6154	Non-discrete measurement name	C an..70	N	Not used
C174	Value/range	C	R	
6411	Measurement unit code	M an..3	M an..3	Use UN/ECE Recommendation 20, for example KGM kilogram
6314	Measure	C an..18	R an..18	
6162	Range minimum quantity	C n..18	N	Not used
6152	Range maximum quantity	C n..18	N	Not used
6432	Significant digits quantity	C n..2	N	Not used
7383	Surface or layer code	C an..3	N	Not used

Remark:**Example:**

MEA+WT+G+KGM: 500 '

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0400		SG10	C	99	3	Equipment
0420	60	MEA	R	1	4	Chargeable weight

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
MEA				
6311	Measurement purpose code qualifier	M an..3	M an..3	CHW Chargeable weight
C502	Measurement details	C	N	
6313	Measured attribute code	C an..3	N	Not used
6321	Measurement significance code	C an..3	N	Not used
6155	Non-discrete measurement name code	C an..17	N	Not used
6154	Non-discrete measurement name	C an..70	N	Not used
C174	Value/range	C	R	
6411	Measurement unit code	M an..3	M an..3	Use UN/ECE Recommendation 20, for example KGM kilogram
6314	Measure	C an..18	R an..18	
6162	Range minimum quantity	C n..18	N	Not used
6152	Range maximum quantity	C n..18	N	Not used
6432	Significant digits quantity	C n..2	N	Not used
7383	Surface or layer code	C an..3	N	Not used

Remark:

Example:

MEA+CHW++KGM: 500 '

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0400		SG10	C	99	3	Equipment
0420	61	MEA	R	1	4	Volume

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
MEA				
6311	Measurement purpose code qualifier	M an..3	M an..3	VOL Volume
C502	Measurement details	C	N	
6313	Measured attribute code	C an..3	N	Not used
6321	Measurement significance code	C an..3	N	Not used
6155	Non-discrete measurement name code	C an..17	N	Not used
6154	Non-discrete measurement name	C an..70	N	Not used
C174	Value/range	C	R	
6411	Measurement unit code	M an..3	M an..3	Use UN/ECE Recommendation 20. MTQ is recommended MTQ cubic metre
6314	Measure	C an..18	R an..18	
6162	Range minimum quantity	C n..18	N	Not used
6152	Range maximum quantity	C n..18	N	Not used
6432	Significant digits quantity	C n..2	N	Not used
7383	Surface or layer code	C an..3	N	Not used

Remark:**Example:**

MEA+VOL++MTQ:25'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0400		SG10	C	99	3	Equipment
0440	62	SEL	C	1	4	Seal number

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
SEL				
9308	Seal identifier	C an..35	C an..35	
C215	Seal issuer	C	C	
9303	Sealing party name code	C an..3	C an..3	SH Shipper
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
9302	Sealing party name	C an..35	C an..35	
4517	Seal condition code	C an..3	N	Not used
C208	Identity number range	C	N	
7402	Object identifier	M an..35	N	Not used
7402	Object identifier	C an..35	N	Not used

Remark:

Example:

SEL+ISG025457+SH:::Sealing party name'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0570		SG14	C	99	3	Goods item details
0580	63	GID	M	1	3	Goods item details

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
GID					
1496	Goods item number	C n..5	R n..5	sequential number	
C213	Number and type of packages	C	R		
7224	Package quantity	C n..8	R n..8		
7065	Package type description code	C an..17	R an..17		
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
7064	Type of packages	C an..35	R an..35		
7233	Packaging related description code	C an..3	C an..3		
C213	Number and type of packages	C	N		
7224	Package quantity	C n..8	N	Not used	
7065	Package type description code	C an..17	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
7064	Type of packages	C an..35	N	Not used	
7233	Packaging related description code	C an..3	N	Not used	
C213	Number and type of packages	C	N		
7224	Package quantity	C n..8	N	Not used	
7065	Package type description code	C an..17	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
7064	Type of packages	C an..35	N	Not used	
7233	Packaging related description code	C an..3	N	Not used	
C213	Number and type of packages	C	N		
7224	Package quantity	C n..8	N	Not used	
7065	Package type description code	C an..17	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
7064	Type of packages	C an..35	N	Not used	
7233	Packaging related description code	C an..3	N	Not used	
C213	Number and type of packages	C	N		
7224	Package quantity	C n..8	N	Not used	
7065	Package type description code	C an..17	N	Not used	
1131	Code list identification code	C an..17	N	Not used	
3055	Code list responsible agency code	C an..3	N	Not used	
7064	Type of packages	C an..35	N	Not used	

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
7233	Packaging related description code	C an..3	N	Not used

Remark:

Example:

GID+1+1:PLT:::Package:761699'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
	0570	SG14	C	99	3	Goods item details
	0590	64 HAN	C	1	4	Handling instructions

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
HAN				
C524	Handling instructions	C	R	
4079	Handling instruction description code	C an..3	R an..3	0 non-stackable 1 stackable
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
4078	Handling instruction description	C an..70	R an..70	Stacking factor
C218	Hazardous material	C	N	
7419	Hazardous material category name code	C an..7	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
7418	Hazardous material category name	C an..35	N	Not used

Remark:

Example:

HAN+1:::2'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
	0570	SG14	C	99	3	Goods item details
	0610	65 DGS	C	9	4	Dangerous goods

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DGS				
8273	Dangerous goods regulations code	C an..3	C an..3	ADR European agreement on the international carriage of dangerous goods on road (ADR) ADS NDR European agreement for the transport of dangerous goods on the river Rhine ADT CA, Transport Canada's dangerous goods requirements ADU JP, Japanese maritime safety agency dangerous goods regulation code AGS DE, ADR and GGVS combined regulations for combined transport ANR ADNR, Autorisation de transport de matieres Dangereuses pour la Navigation sur le Rhin ARD DE, ARD and RID - Combined regulations for combined transport CFR US, 49 Code of federal regulations COM DE, ADR, RID, GGVS and GGVE - Combined regulations for combined transport GVE DE, GGVE (Gefahrgutverordnung Eisenbahn) GVS DE, GGVS (Gefahrgutverordnung Strasse) ICA IATA ICAO IMD IMO IMDG code RGE DE, RID and GGVE, Combined regulations for combined transport on rails RID Railroad dangerous goods book (RID) UI UK IMO book ZZZ Mutually defined
C205	Hazard code	C	R	
8351	Hazard identification code	M an..7	M an..7	3 Flammable and Combustible Liquids 7 Radioactive Materials 8 Corrosives
8078	Additional hazard classification identifier	C an..7	N	Not used
8092	Hazard code version identifier	C an..10	N	Not used
C234	UNDG information	C	R	
7124	United Nations Dangerous Goods (UNDG) identifier	C n4	C n4	
7088	Dangerous goods flashpoint description	C an..8	N	Not used
C223	Dangerous goods shipment flashpoint	C	N	
7106	Shipment flashpoint degree	C n3	N	Not used
6411	Measurement unit code	C an..3	N	Not used
8339	Packaging danger level code	C an..3	N	Not used
8364	Emergency procedure for ships identifier	C an..6	N	Not used

No = Consecutive segment number
MaxOcc = Maximum occurrence of the segment/group
Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
O=Optional, F=Floating, D=Dependent, A=Advised,
S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
8410	Hazard medical first aid guide identifier	C an..4	N	Not used
8126	Transport emergency card identifier	C an..10	N	Not used
C235	Hazard identification placard details	C	N	
8158	Orange hazard placard upper part identifier	C an..4	N	Not used
8186	Orange hazard placard lower part identifier	C an4	N	Not used
C236	Dangerous goods label	C	N	
8246	Dangerous goods marking identifier	C an..4	N	Not used
8246	Dangerous goods marking identifier	C an..4	N	Not used
8246	Dangerous goods marking identifier	C an..4	N	Not used
8255	Packing instruction type code	C an..3	N	Not used
8325	Hazardous means of transport category code	C an..3	N	Not used
8211	Hazardous cargo transport authorisation code	C an..3	N	Not used

Remark:

in case of dangerous goods

Example:

DGS+ADR+3+3394'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0570		SG14	C	99	3	Goods item details
0620	66	FTX	C	10	4	Dangerous goods additional information

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
FTX				
4451	Text subject code qualifier	M an..3	M an..3	AAC Dangerous goods additional information
4453	Free text function code	C an..3	N	Not used
C107	Text reference	C	N	
4441	Free text description code	M an..17	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used
C108	Text literal	C	R	
4440	Free text	M an..512	M an..512	
4440	Free text	C an..512	C an..512	
4440	Free text	C an..512	C an..512	
4440	Free text	C an..512	C an..512	
4440	Free text	C an..512	C an..512	
3453	Language name code	C an..3	N	Not used
4447	Free text format code	C an..3	N	Not used

Remark:

Free Text should contain the HS code

Example:

FTX+AAC+++UN3363, GEFAHRGUT IN GERÄTEN, 9, Transport nach 1.1.4.2.1:UN3363, Dangerous goods in apparatus, 9, carriage in accordance with 1.1.4.2.1:Notfallrufnummer(24h) (GBK ContractID???:93866)???:(001)352 323 3500:DG:Fibreboard Box?:0.5 L'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
	0630	SG15	R	1	4	Gross weight
	0640	MEA	M	1	4	Measurements

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
MEA				
6311	Measurement purpose code qualifier	M an..3	M an..3	WT Weights
C502	Measurement details	C	R	
6313	Measured attribute code	C an..3	R an..3	G Gross weight
6321	Measurement significance code	C an..3	N	Not used
6155	Non-discrete measurement name code	C an..17	N	Not used
6154	Non-discrete measurement name	C an..70	N	Not used
C174	Value/range	C	R	
6411	Measurement unit code	M an..3	M an..3	Use UN/ECE Recommendation 20, for example KGM kilogram
6314	Measure	C an..18	R an..18	
6162	Range minimum quantity	C n..18	N	Not used
6152	Range maximum quantity	C n..18	N	Not used
6432	Significant digits quantity	C n..2	N	Not used
7383	Surface or layer code	C an..3	N	Not used

Remark:**Example:**

MEA+WT+G+KGM: 500 '

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0630		SG15	R	1	4	Volume
0640	68	MEA	M	1	4	Measurements

		Standard	Implementation		
Tag	Name	St Format	St Format	Usage / Remark	
MEA					
6311	Measurement purpose code qualifier	M an..3	M an..3	VOL Volume	
C502	Measurement details	C	N		
6313	Measured attribute code	C an..3	N	Not used	
6321	Measurement significance code	C an..3	N	Not used	
6155	Non-discrete measurement name code	C an..17	N	Not used	
6154	Non-discrete measurement name	C an..70	N	Not used	
C174	Value/range	C	R		
6411	Measurement unit code	M an..3	M an..3	Use UN/ECE Recommendation 20. MTQ is recommended MTQ cubic metre	
6314	Measure	C an..18	R an..18		
6162	Range minimum quantity	C n..18	N	Not used	
6152	Range maximum quantity	C n..18	N	Not used	
6432	Significant digits quantity	C n..2	N	Not used	
7383	Surface or layer code	C an..3	N	Not used	

Remark:**Example:**

MEA+VOL++MTQ:25'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0660		SG16	R	1	4	Dimensions
0670	69	DIM	M	1	4	Dimensions

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DIM				
6145	Dimension type code qualifier	M an..3	M an..3	1 Gross dimensions
C211	Dimensions	M	M	
6411	Measurement unit code	M an..3	M an..3	Use UN/ECE Recommendation 20, for example MTR metre
6168	Length measure	C n..15	R n..15	
6140	Width measure	C n..15	R n..15	
6008	Height measure	C n..15	R n..15	

Remark:**Example:**

DIM+1+MTR:1.00:1.5:2.05'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0690		SG17	R	1	4	Article number customer list
0700	70	PCI	M	1	4	Package identification

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
PCI				
4233	Marking instructions code	C an..3	R an..3	11 Mark article number customer
C210	Marks & labels	C	N	
7102	Shipping marks description	M an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
8275	Container or package contents indicator code	C an..3	N	Not used
C827	Type of marking	C	N	
7511	Marking type code	M an..3	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used

Remark:**Example:**

PCI+11'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0690		SG17	R	1	4	Article number customer list
0710	71	GIN	R	9999	5	Goods identity number

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
GIN				
7405	Object identification code qualifier	M an..3	M an..3	PN Part number
C208	Identity number range	M	M	
7402	Object identifier	M an..35	M an..35	Article number Send the value „dummy“ in case the Bosch article number is not yet available when the initial IFTSTA (S00) is sent.
7402	Object identifier	C an..35	N	Not used
C208	Identity number range	C	C	
7402	Object identifier	M an..35	M an..35	Article description
7402	Object identifier	C an..35	N	Not used
C208	Identity number range	C	N	
7402	Object identifier	M an..35	N	Not used
7402	Object identifier	C an..35	N	Not used
C208	Identity number range	C	N	
7402	Object identifier	M an..35	N	Not used
7402	Object identifier	C an..35	N	Not used
C208	Identity number range	C	N	
7402	Object identifier	M an..35	N	Not used
7402	Object identifier	C an..35	N	Not used

Remark:

Example:

GIN+PN+0601703703+Lagerflansch'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0690		SG17	C	1	4	Position reference number
0700	72	PCI	M	1	4	Package identification

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
PCI				
4233	Marking instructions code	C an..3	R an..3	21 Line item only
C210	Marks & labels	C	R	
7102	Shipping marks description	M an..35	M an..35	
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
8275	Container or package contents indicator code	C an..3	N	Not used
C827	Type of marking	C	N	
7511	Marking type code	M an..3	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used

Remark:

Example:

PCI+21+123456789'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0690		SG17	C	1	4	Packaging material number
0700	73	PCI	M	1	4	Package identification

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
PCI				
4233	Marking instructions code	C an..3	R an..3	26 Shipper assigned skid number
C210	Marks & labels	C	R	
7102	Shipping marks description	M an..35	M an..35	
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
8275	Container or package contents indicator code	C an..3	N	Not used
C827	Type of marking	C	N	
7511	Marking type code	M an..3	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used

Remark:**Example:**

PCI+26+packtype '

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0690		SG17	C	999	4	Package identification
0700	74	PCI	M	1	4	Package identification

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
PCI				
4233	Marking instructions code	C an..3	R an..3	30 Mark serial shipping container code
C210	Marks & labels	C	C	
7102	Shipping marks description	M an..35	M an..35	
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
7102	Shipping marks description	C an..35	N	Not used
8275	Container or package contents indicator code	C an..3	N	Not used
C827	Type of marking	C	N	
7511	Marking type code	M an..3	N	Not used
1131	Code list identification code	C an..17	N	Not used
3055	Code list responsible agency code	C an..3	N	Not used

Remark:**Example:**

PCI+30+HU ident'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0690		SG17	C	999	4	Package identification
0710	75	GIN	C	1	5	Goods identity number

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
GIN				
7405	Object identification code qualifier	M an..3	M an..3	BN Serial number
C208	Identity number range	M	M	
7402	Object identifier	M an..35	M an..35	
7402	Object identifier	C an..35	N	Not used
C208	Identity number range	C	N	
7402	Object identifier	M an..35	N	Not used
7402	Object identifier	C an..35	N	Not used
C208	Identity number range	C	N	
7402	Object identifier	M an..35	N	Not used
7402	Object identifier	C an..35	N	Not used
C208	Identity number range	C	N	
7402	Object identifier	M an..35	N	Not used
7402	Object identifier	C an..35	N	Not used
C208	Identity number range	C	N	
7402	Object identifier	M an..35	N	Not used
7402	Object identifier	C an..35	N	Not used

Remark:
RFID tag

Example:
GIN+BN+RFID'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0720	76	UNT	M	1	0	Message trailer

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
UNT				
0074	Number of segments in the message	M n..6	M n..6	
0062	Message reference number	M an..14	M an..14	

Remark:

Example:

UNT+74s+1'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Status message for LSP services

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0000	77	UNZ	M	1	0	Interchange trailer

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
UNZ				
0036	Interchange control count	M n..6	M n..6	
0020	Interchange control reference	M an..14	M an..14	

Remark:

Example:

UNZ+1+3518'

Counter = Counter of segment/group within the standard
 No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)



Status message for LSP services

Example message

No. Tag	Example
0000 UNA	UNA:+. ? ' '
0000 UNB	UNB+UNOC:3+technical sender ID+LSP_Services+200722:1033+3518'
0010 UNH	UNH+1+IFTSTA:D:01C:UN'
0020 BGM	BGM+7+78901234+9'
0030 DTM	DTM+137:20200722:102'
0040 TSR	TSR+27+AIR+A03'
SG1	
0060 NAD	NAD+MS+GS1COMPANYID++CARRIER COMPANY:EDI+STREET+CITY++12345+DE '
SG1	
0060 NAD	NAD+MR+++ROBERT BOSCH GMBH:ZENTRALLAGER DEUTSCHLAND+MITTELRHEI NSTR. 19+WORMS++67550+DE'
SG4	
0170 CNI	CNI+1+12345-ABC7890123'
SG5	
0210 STS	STS+1+S02+C05:::Reason code text'
0220 RFF	RFF+HB:HAMA55045'
0220 RFF	RFF+BL:COSU6257279340'
0220 RFF	RFF+HA:232323'
0220 RFF	RFF+MA:15746714673'
0220 RFF	RFF+PL:121212'
0220 RFF	RFF+BN:12AB34CD'
0220 RFF	RFF+EQ:TEMU6982560'
0220 RFF	RFF+SRN:SHD-97673'
0220 RFF	RFF+DQ:5/SEXP/20/WZ'
0220 RFF	RFF+CR:20008868992B01017115'
0220 RFF	RFF+ON:4200001234:0001'
0220 RFF	RFF+IV:5/SEXP/01/20/FV'
0220 RFF	RFF+MRN:20DE755324047503E6'
0220 RFF	RFF+ABT:ATB150059680320202325/3'
0220 RFF	RFF+CC:ATB150059680320202325/3'
0220 RFF	RFF+TOD:FCA'
0220 RFF	RFF+LOC:Hamburg'
0220 RFF	RFF+WR:I-26943525'
0220 RFF	RFF+ATT:bbuf909911sfd'
0220 RFF	RFF+FF:04310394173'
0220 RFF	RFF+TO:676767'
0220 RFF	RFF+LO:787878'

Status message for LSP services

Example message

No. Tag	Example
0220 RFF	RFF+CT:NON-CONTRACTED'
0230 DTM	DTM+9:202004141316:203'
0230 DTM	DTM+76:202004151316:203'
0230 DTM	DTM+11:202004151316:203'
0230 DTM	DTM+2:202004151316:203'
0250 FTX	FTX+TRA+++Free text comment'
0250 FTX	FTX+AGK+++http?://www.ednpoint-dp.com'
0250 FTX	FTX+SAF+++Y'
0250 FTX	FTX+CEX+++Y'
0250 FTX	FTX+CIP+++Y'
SG6	
0270 NAD	NAD+PW+989898+name+description as depot ID+address+city++postal code+FR'
SG6	
0270 NAD	NAD+DP+444555+name+description as depot ID+address+city++postal code+FR'
SG6	
0270 NAD	NAD+CZ+PLPIW001+name+description as depot ID+address+city++postal code+FR'
SG6	
0270 NAD	NAD+CN+CNBO005+name+description as depot ID+address+city++postal code+FR'
SG6	
0270 NAD	NAD+FP+CNBO005+name+description as depot ID+address+city++postal code+FR'
SG6	
0270 NAD	NAD+SC+456789+name++address+city++postal code+FR'
SG6	
0270 NAD	NAD+RF++++address+city++postal code+FR'
SG6	
0270 NAD	NAD+EL+DEHAM++POL'
SG6	
0270 NAD	NAD+EL+CHSHA++POD'
SG6	
0270 NAD	NAD+CS+71019878+name++address+city++postal code+FR'
SG6	
0270 NAD	NAD+CB+654456+name++address+city++postal code+FR'
SG6	

Status message for LSP services

Example message

No. Tag	Example
0270 NAD	NAD+FW+4546323+name++address+city++postal code+FR'
SG6	
0270 NAD	NAD+CA+234245+name++address+city++postal code+FR'
0310 LOC	LOC+172++52.49.38N 13.41.37E'
SG8	
0340 TDT	TDT+21++10:SEA+13:008E+MAEU:::MAERSK+++30:::MSC Bosch'
SG10	
0410 EQD	EQD+CN+TEMU6982560+45G1:::5:45G1+++FLL'
0420 MEA	MEA+WT+G+KGM:500'
0420 MEA	MEA+CHW++KGM:500'
0420 MEA	MEA+VOL++MTQ:25'
0440 SEL	SEL+ISG025457+SH:::Sealing party name'
SG14	
0580 GID	GID+1+1:PLT:::Package:761699'
0590 HAN	HAN+1:::2'
0610 DGS	DGS+ADR+3+3394'
0620 FTX	FTX+AAC+++UN3363, GEFAHRGUT IN GERÄTEN, 9, Transport nach 1.1.4.2.1:UN3363, Dangerous goods in apparatus, 9, carriage in accordance with 1.1.4.2.1:Notfallrufnummer(24h) (GBK ContractID???:93866)???:(001)352 323 3500:DG:Fibreboard Box?:0.5 L'
SG15	
0640 MEA	MEA+WT+G+KGM:500'
SG15	
0640 MEA	MEA+VOL++MTQ:25'
SG16	
0670 DIM	DIM+1+MTR:1.00:1.5:2.05'
SG17	
0700 PCI	PCI+11'
0710 GIN	GIN+PN+0601703703+Lagerflansch'
SG17	
0700 PCI	PCI+21+123456789'
SG17	
0700 PCI	PCI+26+packtype'
SG17	
0700 PCI	PCI+30+HU ident'
0710 GIN	GIN+BN+RFID'
0720 UNT	UNT+74+1'
0000 UNZ	UNZ+1+3518'

Status message for LSP services

Change history

Date	Changes																																													
18.03.2021	Initial version																																													
10.05.2021	Version 2 RFF+DQ R => D RFF+ON R => D RFF+IV R => D RFF+TOD R => D RFF+LOC R => D DTM+9 R => D DTM+76 C => D DTM+11 R => D DTM+2 R => D NAD+RF C => D NAD+EL (POL) R => D NAD+EL (POD) R => D GIN+PN C => R TSR segment adapted EQD segment adapted SG17 (article number customer list) C => R GIN+PN adapted																																													
17.06.2021	Verison 3 New RFF+SRN SG10 new MEA segments SG14 deletion MEA chargeable weights Several hints regarding references to IFCSUM message																																													
20.03.2023	Version 4 TSR D_4065 new codes																																													
25.07.2023	Version 5 <table border="0"> <tr> <td>NAD+PW</td> <td>C080</td> <td>C => D; Remark: mandatory for status events starting from S45</td> </tr> <tr> <td>NAD+DP</td> <td>C059</td> <td>C => D; Remark: mandatory for status events starting from S45</td> </tr> <tr> <td>NAD+CZ</td> <td>3164</td> <td>C => D; Remark: mandatory for status events starting from S45</td> </tr> <tr> <td>NAD+CN</td> <td>3251</td> <td>C => D; Remark: mandatory for status events starting from S45</td> </tr> <tr> <td>NAD+FP</td> <td>3207</td> <td>C => D; Remark: mandatory for status events starting from S45</td> </tr> <tr> <td> </td> <td> </td> <td> </td> </tr> <tr> <td>TSR</td> <td>C536 4065</td> <td>is defined as "R".</td> </tr> <tr> <td> </td> <td> </td> <td> </td> </tr> <tr> <td>TDT</td> <td>C222 8213</td> <td>C => D; Remark: mandatory for transport name code "30" and "40" and for status events S04, S07, S16</td> </tr> <tr> <td> </td> <td> </td> <td> </td> </tr> <tr> <td>EQD</td> <td>C224 8155</td> <td>C => D; Remark: mandatory for sea freight BCO and FCL</td> </tr> <tr> <td> </td> <td> </td> <td>3 stacked ==> 0 non-stackable</td> </tr> <tr> <td>HAN</td> <td>C524 4079</td> <td>1 stackable</td> </tr> <tr> <td> </td> <td> </td> <td> </td> </tr> <tr> <td>RFF+CT(new)</td> <td>in SG5</td> <td>status D if shipment is non contracted (e.g. SPOT) fill this field with "NON-CONTRACTED" or "SPOT"</td> </tr> </table>	NAD+PW	C080	C => D; Remark: mandatory for status events starting from S45	NAD+DP	C059	C => D; Remark: mandatory for status events starting from S45	NAD+CZ	3164	C => D; Remark: mandatory for status events starting from S45	NAD+CN	3251	C => D; Remark: mandatory for status events starting from S45	NAD+FP	3207	C => D; Remark: mandatory for status events starting from S45				TSR	C536 4065	is defined as "R".				TDT	C222 8213	C => D; Remark: mandatory for transport name code "30" and "40" and for status events S04, S07, S16				EQD	C224 8155	C => D; Remark: mandatory for sea freight BCO and FCL			3 stacked ==> 0 non-stackable	HAN	C524 4079	1 stackable				RFF+CT(new)	in SG5	status D if shipment is non contracted (e.g. SPOT) fill this field with "NON-CONTRACTED" or "SPOT"
NAD+PW	C080	C => D; Remark: mandatory for status events starting from S45																																												
NAD+DP	C059	C => D; Remark: mandatory for status events starting from S45																																												
NAD+CZ	3164	C => D; Remark: mandatory for status events starting from S45																																												
NAD+CN	3251	C => D; Remark: mandatory for status events starting from S45																																												
NAD+FP	3207	C => D; Remark: mandatory for status events starting from S45																																												
TSR	C536 4065	is defined as "R".																																												
TDT	C222 8213	C => D; Remark: mandatory for transport name code "30" and "40" and for status events S04, S07, S16																																												
EQD	C224 8155	C => D; Remark: mandatory for sea freight BCO and FCL																																												
		3 stacked ==> 0 non-stackable																																												
HAN	C524 4079	1 stackable																																												
RFF+CT(new)	in SG5	status D if shipment is non contracted (e.g. SPOT) fill this field with "NON-CONTRACTED" or "SPOT"																																												

Change history
